

TX-5011-03-1

Shock sensor 868 MHz Gen2, white

The shock sensor is designed to detect the vibrations made by an intruder trying to break a window or door. The sensor has an internal reed allowing to supervise a door or window using the door magnet that is included.

Sensitivity and pulse count options can be set using DIP switches. A jumper allows to select which reed is in use (left or right or none). In walk-test mode, the blue LED on the front cover will light up when the sensor is in alarm state.



Details

- Learn-Mode technology
- Supervised transmissions
- LED indicating sensor status
- Detects opening of door or window
- Magnet included
- Gross attack and pulse count detection modes

TX-5011-03-1

Shock sensor 868 MHz Gen2, white

Technical specifications

General

Product type	Magnetic Contact, Shock with analyser
--------------	---------------------------------------

Wired/wireless

Wired-wireless	Wireless
----------------	----------

Wireless frequency	868 MHz AM
--------------------	------------

Electrical

Current consumption	10 μ A (typical standby)
---------------------	------------------------------

Batteries	1 x 3 V Lithium
-----------	-----------------

Battery lifetime	3 to 5 years
------------------	--------------

Physical

Physical dimensions	114 x 32 x 32 mm
---------------------	------------------

Colour	White
--------	-------

Compatible with

Interlogix 868 MHz Gen2 receivers



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 30 July 2020 - 16:51