

# PM862

## Fuente de alimentación 24Vcc/1,5A.

---

This efficiency cost effective power supply is ideal for use in Fire, Access control and general security applications.

---

Featuring a regulated 27.6 Vdc output supplying continuous full rated current to load plus additional current for charging two x 12V standby batteries.

---

The highly efficient switch mode design ensures low operating costs, generates less heat and with a small physical size increases the room available for additional PCBs or cables. The modular construction simplifies maintenance.



### Details

---

- Fault and mains present indicators
- Battery disconnect to prevent deep discharge
- Tamper switch
- Fault outputs
- Mains and dc fuse
- Powder coated steel housing

# PM862

## Fuente de alimentación 24Vcc/1,5A.

### Technical specifications

---

#### General

Fusible(s)	230 VAC input 2 A, 12/24 V output 2 A
------------	---------------------------------------

---

#### Eléctrico

Entrada principal	230 VAC 50 Hz $\pm$ 10%
-------------------	----------------------------

---

#### Salida

Voltaje de la salida de potencia	27,6 VCC
Ondulación de salida	100 mV pk-pk max.
Corriente de salida principal	2 A

---

#### Batería

Máx. capacidad de la batería	7.2 Ah (x2)
Corriente de carga de la batería	0.5 A
Tiempo de recarga de la batería	20 hours
Voltaje de desconexión de la batería	19.6 $\pm$ 0.2 VDC

---

#### Físico

Dimensiones físicas	330 x 275 x 80 mm (W x H x D)
Color	Blanco
Factor de forma	Armario de acero

---

#### Medioambiental

Temperatura de funcionamiento	-10 to +40°C
Humedad relativa	95%

---

#### Estándares y Regulaciones

Cumplimiento	CE, REACH, RoHS 2, WEEE
--------------	-------------------------

---

#### Load output

1.5 A
-------

---

#### Open collector output

Open circuit on fault or mains fail - 0 V - 100 mA
--

---

#### Housing (steel) powder coated

1.2 mm
--------

---

